

VIBRATION RANGE

i-SPYDER PISTOL

Pistol-type electronic integrated converter

The pistol SPYDER vibrators offer the same benefits of the standard SPYDER range but with the added ergonomics and manageability advantage that the pistol handle offers.




- Vibration frequency 12,000 v.p.m.
- Optional rubber poker end
- Standard voltage/frequency input: 230v~50/60Hz (Optionally available in 110v~50/60Hz, upon request)
- Standard lengths: 0.8m transmission and 15m cable (other lengths available)
- Progressive start to avoid current peaks, preventing deterioration
- Tricolor external LED indicator to communicate any incident to the user (For i-Spyder Button)



Technical Data

MODEL	Total weight (kg)	Length (mm)	Diameter (mm)	Power of input (kW)	Performance (m3/h)
i-SPYDER 230V-30	11.5	353	30	0.4	Up to 10
i-SPYDER 230V-38	13	370	38	0.75	Up to 20
i-SPYDER 230V-50	17	365	50	1.1	Up to 30
i-SPYDER 230V-60	19	400	58	1.5	Up to 35
i-SPYDER 230V-70	21	412	66	1.9	Up to 40

*All the i-SPYDERs are available both in Switch version and Button version.



+ Plug & Play

Converter and poker integrated in a ready-to-use kit.



+ Ergonomic

The pistol handle brings a great manageability and ergonomics to the user, specifically designed for conditions which require a great user's mobility.



+ Light and compact

Lightweight and manageable, can be used in places of difficult access and handled by a single operator.



+ Safe and reliable

Hermetic protective housing that protects it against water and dust (IP67). Electrical protection against overloads, overvoltage, short circuits...